JADE BIRD FIRE ALARM SYSTEMS

BY-Z2145E

Emergency Exit Signal




Key Features

- Easy to install
- Multiple outlets
- Long battery life
- Safety and performance in accordance with IEC 60598-2-22
- CE Certificate

BY-Z2145E exit signal can be installed on walls. It is particularly suitable for interiors such as offices, schools, universities and hospitals but the IP protection grade makes the unit also suitable for outdoors. It incorporates a green LED indicator that shows battery charging mode. Safety and performance according to EN 55015, EN 61347, EN 60598-1, EN 60598-2-22, EN 61000-3-2, EN 61000-3-3. The built-in battery unit ensures an emergency operation period higher than 3 hours.

	TECHNICAL DATA	
Input	220-240 VAC - 50 Hz - 0,05A	
Light source	27 x 0,2 watt white LED	
Input power	4.5W	
Luminous flux	> 140 Lumens	
CCT	6500k	
Power factor	0.52	
Battery	Ni-Cd SC3.6V 1.5Ah	
Discharge duration	>3h	
Degree of protection	IP65	
Case materials	Poly carbonate	
Dimension (WxHxD)	352 mm x 110 mm x 68 mm	
Weight	0.7 kg	
Model List		
Model No.	Operating mode	Direction
BY-Z2145E-M	Maintained	Right, Left, Down
BY-Z2145E-N	Non-Maintained	Right, Left, Down

Mechanical dimensions (all dimensions in mm)



Installation

